

Satellite Multiswitch 9/8 MK-Digital MV 908 Cascadable

Item number: 5490

2 Sat --> 8 participants

119,90 €

incl. VAT, plus shipping costs

Delivery status: At the moment not on stock.

Open product

www.ariasat.de

Product description

MK Digital MV 908 Multiswitch 9 to 8 cascadable

• Multi-switch can be used as a single device or end cascade.

• Feeding of terrestrial signals possible (active or passive).

• Independent program diversity for all participants of the reception system

• Very low pass-through attenuation of the satellit …

Technical data

• Input frequency: SAT 950...2150 MHz
• Terr. 18...862 MHz
• Inputs: 8 SAT, 1 TERR
• Outputs: 8 for receivers or subscribers
• Attenuation SAT 950...2150 MHz: -1....-3dB
• Connection attenuation Terr. 47...862 MHz (Active): -16....-7 dB
• Port attenuation Terr. 5...862 MHz (Passive)): -38....-28 dB
• Switching criteria: DISEqC 2.0/13V,18V,13V+22K …
• Decoupling H/V: 30 dB typ.
• Return loss (applies to input and output) SAT / Terr.: 10 dB typ.
• Input level SAT: 95 dBµV max.
• Output level SAT: 100 dBµV max
• Output level Terr.: 92 dBµV max
• DC current consumption from receiver: 40 mA
• Operating temperature: 0...+55 °C
• Operating voltage: 90 …

Ariasat Digital Sat-Systems e.K. · Inhaber: Zeki Sevinc
Keplerstr. 96 · 41236 Mönchengladbach · Deutschland · Tel. +49 (0)2166 621419 · info@ariasat.de · www.ariasat.de
Amtsgericht Mönchengladbach · HRA 4969 · USt-IdNr. DE217691629 · WEEE-Reg.-Nr. DE72606496 · LUCID DE4476101328140

Automatically generated product information. Price, delivery time and availability in the online shop are authoritative. Changes and errors excepted.
QR code or product link opens the current product page in the Ariasat online shop.